INTRODUCTION TO ROBOTICS

(Kinematics, Dynamics, and Design)

SESSION # 12:

MANIPULATOR


INVERSE KINEMATICS


Ali Meghdari, Professor

School of Mechanical Engineering Sharif University of Technology Tehran, IRAN 11365-9567


Homepage: http://meghdari.sharif.edu







- Forward Kinematics: Describe the position and orientation of the manipulator's end-effector as a function of joint variables relative to a base frame.
- Inverse Kinematics: Given the desired position and orientation of the end-effector relative to the base, compute the set of joint variables which will achieve this desired result.




A 3-DOF Manipulator Arm



Inverse Kinematics

How do I put my hand here?



Inv. Kin.: Choose these angles!



• Solvability (قابل حل بودن):

Solving kinematics equations in robotics is a Non-Linear Problem.

Given; ${}^{0}T_{n}$, Find; $\{\theta_{1}, \theta_{2}, ..., \theta_{n}\}$, is a *non-linear* problem.

Ex: PUMA-560 Robot. Given; ${}_{6}^{0}T$, Find; $\{\theta_1, \theta_2, ..., \theta_6\}$?

$$\begin{split} r_{11} &= C_1 [C_{23} (C_4 C_5 C_6 - S_4 S_6) - S_{23} S_5 C_6] + S_1 (S_4 C_5 C_6 + C_4 S_6), \\ r_{21} &= S_1 [C_{23} (C_4 C_5 C_6 - S_4 S_6) - S_{23} S_5 C_6] - C_1 (S_4 C_5 C_6 + C_4 S_6), \\ r_{31} &= -S_{23} (C_4 C_5 C_6 - S_4 S_6) - C_{23} S_5 C_6, \end{split}$$

• • •

Equation: (3.14)



• Solvability (قابل حل بودن):

For a 6-DOF manipulator, we have:
$${}_{0}^{0}T =$$

 ${}_{6}^{0}T = \begin{bmatrix} r_{11} & r_{12} & r_{13} & p_{x} \\ r_{21} & r_{22} & r_{23} & p_{y} \\ r_{31} & r_{32} & r_{33} & p_{z} \\ \hline 0 & 0 & 0 & 1 \end{bmatrix}$

- 12-Equations, and 6-Unknowns?
- From 9-Equations of the Rotation Matrix, only 3-Equations are independent.
- Therefore, we have 6-independent non-linear equations and 6-unknowns.



A manipulator is *solvable* if the joint variables can be determined by an algorithm. This algorithm should find all possible solutions.

We have 6-independent non-linear equations and 6unknowns. Therefore, we should investigate the followings:

- > Existence of Solution (وجود جواب) .
- > Multiple Solutions (تعدد جواب ها).
- > Method of Solution (روش حل).



> Existence of Solution (وجود جواب):

Existence of solution to Inv.-Kin. problem depends on the existence of the specified goal point in the manipulator's Workspace.


Workspace/Work-envelope(ففای کاری): is that volume of space which the end-effector of a robot can reach.

Dexterous Workspace(فضای کاری ماهر): is that volume of space which the end-effector of a robot can reach with all orientations.



· Solvability (قابل حل بودن):


Reachable Workspace (فضاى كارى قابل دسترس) : is that volume of space which the end-effector of a robot can reach with at least one orientations.





> Workspace (فضای کاری قابل دسترس):

To describe Manipulator's
Work Space: Compute direct
kinematics, vary joint variables
within their range of motion,
and then sketch the results.





• Example: Consider the workspace of a two-

link planar manipulator.


If $\ell_1 = \ell_2$, then:

Reachable Workspace is;

Disk of Radius = $2\ell_1 = 2\ell_2$

Dexterous Workspace is;

Origin.



 $\theta_2 \equiv 0 - 360^\circ$



• Example: Consider the workspace of a twolink planar manipulator.

If $\ell_1 \neq \ell_2$ and $\ell_1 > \ell_2$ then:

Reachable Workspace is;


A Disk as shown:

$$Outer - Radius \equiv \ell_1 + \ell_2$$

$$Inner - Radius \equiv |\ell_1 - \ell_2|$$

Dexterous Workspace does

not exist.





• Example: For the end-effector of this robot to reach all points within its workspace, what should be the links lengths?

$$OR \equiv R_2 = \ell_1 + \ell_2$$

$$IR \equiv R_1 = |\ell_1 - \ell_2|$$

• If $\ell_1 > \ell_2$ then:

$$R_1 + R_2 = (\ell_1 - \ell_2) + (\ell_1 + \ell_2) \Rightarrow \ell_1 = \frac{R_1 + R_2}{2}, \quad and$$

$$\ell_2 = R_2 - \ell_1 = R_2 - \frac{R_1 + R_2}{2} = \frac{R_2 - R_1}{2}$$

• If $\ell_1 < \ell_2$ then:

$$R_1 + R_2 = -(\ell_1 - \ell_2) + (\ell_1 + \ell_2) \Rightarrow \ell_2 = \frac{R_1 + R_2}{2}, \quad and$$

$$\ell_1 = R_2 - \ell_2 = R_2 - \frac{R_1 + R_2}{2} = \frac{R_2 - R_1}{2}$$



Example: Planar 3-link robot


$$x = l_{1} \cos \theta_{1} + l_{2} \cos(\theta_{1} + \theta_{2}) + l_{3} \cos(\theta_{1} + \theta_{2} + \theta_{3})$$

$$y = l_{1} \sin \theta_{1} + l_{2} \sin(\theta_{1} + \theta_{2}) + l_{3} \sin(\theta_{1} + \theta_{2} + \theta_{3})$$

$$\phi = \theta_{1} + \theta_{2} + \theta_{3}$$

$$\text{Take } l_{1} > l_{2} > l_{3}, \ l_{1} > l_{2} + l_{3}$$

What is the reachable workspace?






Workspace Comparison


(a) Spherical (RRP)


(b) SCARA (RRP)




(d) Cartesian (3P)















Workspace Comparison

A 3R Elbow Manipulator











• Solvability (قابل حل بودن):

> Multiple Solutions(تعدد جوابها)


A manipulator may reach any position in the interior of its workspace with different configurations. But the system has to be able to choose one.

A manipulator moving from point A to B:

Two solutions exist:

- One causes a collision, and
- Other is safe.


Therefore, we need to find all solutions, and teach the robot to choose the best one.





- Solvability (قابل حل بودن):
- > Multiple Solutions(تعدد جوابها)

Ex: The PUMA-560 manipulator can reach certain goals with 8-different solutions. Due to the limits imposed on joints ranges, some of these solutions may not be accessible.



{Other 4-solutions are for the wrist}



- Solvability (قابل حل بودن):
- > Multiple Solutions(تعدد جوابها):

In general number of solutions depends on the non-zero D-H link parameters, and the allowable rang of motion for the joints.

- The more Non-Zero link parameters _____ The more Solutions to reach a certain goal.
- Up to 16-solutions are possible for a completely general revolute arm with 6-DOF (see table 4.5).



> Methods of Solutions

A manipulator is *solvable* if the joint variables can be determined by an algorithm. This algorithm should find all possible solutions.

- Closed-form solutions
- Numerical solutions

We are interested in closed-form solutions:

- 1. Algebraic Methods
- 2. Geometric Methods

